

Wireless Keyfob

Partcode: KEYFOB-WB / KEYFOB-WD / KEYFOB -WE



RINS1849-2

EN50131-3:2009
EN50131-5-3:2005+A1:2008
Security Grade (SG) 2
Environmental Class (EC) II



EN

Frequency Band (MHz)	Wireless Frequency Indicator
433.050 - 434.790	WB
866.000 - 866.600	WD
868.000 - 868.600	WE

References:

- A** LEARNING FROM DEFAULT: Learning the keyfob is performed in the Manager Menu of the Control Panel.
- B** DELETING: This deletes a keyfob from the control panel.
- C** RE-LEARNING: When a keyfob needs to be learned onto another control panel, with or without deleting the keyfob first, a 're-learn' must be performed instead of a 'learn'.
- D** LEDs: 1) General LEDs: (i) From power up: Not learnt (ii) Learning process. (iii) 8 x flashes: Learnt (iv) Fast flashing: Unlocking. (v) Fast flashing: Locking. (vi) 18 x Slow flashes (10 secs): Fault with new battery installed. (vii) 6 x Flashes: Alarm (when checking status) 2) Arming/Disarming LEDs: (i) Arming. (ii) (Amber) 4 x Flashes: Fault. 1 x Flash: Key pressed. (iii) Armed. (iv) Disarmed.
- E** REPLACING THE BATTERY: When the battery needs replacing please make sure that the positive and negative are as shown in the diagram.

Specification

Button Configurations (all programmable):

⏏, ⏏, I, II, ⏏+⏏, I+II, ⏏+I, and ⏏+II.

Button Actions:

Show status, Arm/Set area, Disarm/Set area, Latch output, Timed output and Personal Attack.

Battery:

Type: 1x Li-Mn Cell 3.0V

Part Code: BATT-KF1215

Threshold: 2.1V +/- 5% at 25°C. Life: Up to 2 Years.

Wireless:

Transmission Frequency: FM Transceiver Narrow Band.

Transmission Method: Fully encrypted rolling code

Code combinations: 4294967295.

Materials and Environment

Indication: LEDs (Red, Green, Amber)

Temperature: Storage: -20°C to 50°C. Certified: -10°C to 40°C. Nominal: -10°C to 50°C.

Dimensions (H x W x D): 72 x 30 x 20mm. Weight: 28g

Compatible with the Enforcer, PCX and EURO commercial control panels (using the Wireless Expander).

Battery Information

The battery supplied has been chosen to provide long service life whilst, for safety reasons, having limited output current.

When disposing of the product, the battery must be removed and disposed of separately in accordance with the local regulations.

Product Information

For electrical products sold within the European Community. At the end of the electrical products life, it should not be disposed of with household waste. Please recycle where facilities exist. Check with your Local Authority or retailer for recycling advice in your country. To prevent possible damage to components, any static charge on your body needs to be eliminated before touching the inside of the unit. This can be accomplished by touching some grounded/earthed metallic conductor such as a radiator/pipework immediately before replacing the battery.

Warranty

This product is sold subject to our standard warranty conditions and is warranted against defects in workmanship for a period of two years (battery excluded). In the interest of continuing care and design, Pyronix Ltd reserves the right to amend specifications, without giving prior notice. Please see the control panel programming manuals for further information or visit: www.pyronix.com/warranty



A LEARNING FROM DEFAULT

UK	EXPORT	ITALIAN
CHANGE CODES?	LEARN USER CODES KEYFOBS & TAGS?	MEMORIZZA CODICI TAG/TELECOMANDI?
Add New User?	User Codes/Tags/Learn Keyfobs?	Memorizza Codici Tag/Telecomandi?
Empty [01]	Empty [01]	Vuoto [01]
Enter User Code []	Enter User Code []	Memorizza []

ITALIAN
Home Utente
Scegli Tasto Tasto [1]
Funzione: [2] Ins.re Area

UK/EXPORT
User Name
Select Button Lock [1]
Button Action[2] Set Area

B DELETING

UK	EXPORT	ITALIAN
CHANGE CODES? YES	LEARN USER CODES KEYFOBS & TAGS? <input checked="" type="checkbox"/>	MEMORIZZA CODICI TAG/TELECOMANDI? <input checked="" type="checkbox"/>
Add New User? NO	User Codes/Tags/Learn Keyfobs? <input checked="" type="checkbox"/>	Memorizza Codici Tag/Telecomandi? <input checked="" type="checkbox"/>
Delete/Change User? YES	Keyfob [01] <input checked="" type="checkbox"/>	Telecomando [01] <input checked="" type="checkbox"/>
Keyfob Dave [03] YES	Enter User Code [*****] <input checked="" type="checkbox"/>	Memorizza [*****] <input checked="" type="checkbox"/>
Delete User? YES	Enter User Code [] <input checked="" type="checkbox"/>	Memorizza [] <input checked="" type="checkbox"/>

C RE-LEARNING

D LEDs 1) General LEDs

- (i) From power up: Not learnt (slow flashing)
- (ii) Learning process (fast flashing)
- (iii) 8 x flashes: Learnt
- (iv) Fast flashing: Unlocking
- (v) Fast flashing: Locking
- (vi) 18 x Slow flashes (10 secs): Fault with new battery installed
- (vii) 6 x Flashes: Alarm (when checking status)

2) Arming/Disarming LEDs

- (i) Arming
- (ii) (Amber) 4 x Flashes: Fault 1 x Flash: Key pressed
- (iii) Armed
- (iv) Disarmed

E REPLACING THE BATTERY

